


The ECSL06 Series are split-core current transformers. The CT can be mounted to existing panels, such as control centers or load centers, to measure or monitor wattage. These CTs can be mounted without removing existing cables for easier installation.




MODEL	INPUT CURRENT	AVAILABLE OUTPUT
ECSL06-20	20 A	CURRENT OUTPUTS @ 20mA, 33.3mA, 40mA, 50mA,100mA,1A VOLTAGE OUTPUTS @ 0.25V, 0.33V, 0.5V, 1V, 2V  (can be customized by customer)
ECSL06-30	30 A	
ECSL06-40	40 A	
ECSL06-50	50 A	
ECSL06-60	60 A	


# STATE LISTS DATE TO SEE THE SECOND SE






# **Mechanical Dimensions in mm**







### **APPLICATIONS**

- Energy and sub-metering products
- Electrical load monitoring
- Network equipment
- Instruments and sensors
- Control systems
- Go GREEN initiatives

# **FEATURES**

- 0.248" window opening (ID)
- Custom design Turns-Ratio available
- Rigid housing case with UL 94V-0 durable plastic
- PVC wire leads—18AWG
- Approximate weight 100g

### **SPECIFICATIONS**

- Standard Input Current 0.1-60A
- Frequency 50Hz 400Hz
- Standard accuracy 0.5,1,3
- Insulation Voltage 4000 Vac/1min
- Operating Temp. -40°C to +70°C
- Storage Temp. -45°C to +85 °C
- UL2808 and IEC61010-1 Standards

# **Connection Diagram**

